



NEW
APPA SFLEX-18T
APPA SFLEX-10T

3000A AC current measurement
 Slide switch to change range
 Voltage output to universal voltage meters
 10/18inch head cable length
 7.5mm coil diameter for tight space measurement
 2 meter extension cable
 Low Batt. LED indicator
 Ergonomically designed one hand operation
 CAT IV 600V/ CAT III 1000V safety standard



NEW
APPA SFLEX-18D
APPA SFLEX-10D

3000A AC current measurement
 3000 count large scale LCD display with backlit
 Auto Ranging
 Data Hold
 10/18inch head cable length
 7.5mm coil diameter for tight space measurement
 Low Batt. Segment indicator
 Ergonomically designed one hand operation
 CAT IV 600V/ CAT III 1000V safety standard



APPA 130F series intergated with APPA SFLEX-T expanding the current range to 3000 ACA, providing increased display flexibility, making electrical measurement easier and safer.

Flexible Current Probe Meter

FEATURES:

	APPA SFLEX-10D/18D	APPA SFLEX-10T/18T
Display	3000 count	N/A
AC Current	0.01A~3000A	0.01A~3000A
Basic Accuracy: at 45 - 500Hz	±(3.0%+5d)	±3% of full scale
Auto Ranging	.	N/A
Measuring Method	TRUE RMS	TRUE RMS
Display Hold	HOLD	N/A
Backlit	.	N/A
Head Cable Length	10/18 inch	10/18 inch
Extension Cable Length	N/A	2 meter
Hand Guard Designed	.	.

GENERAL:

Overload Indication	"OL"	N/A
Low Battery Indication	□	LED
Auto Power Off: Approx. 20 minutes	.	N/A
Operating Temperature: 0°C~50°C, □80% RH	.	.
Storage Temperature: - 20°C ~ 60°C	.	.
Temperature Coefficient: 0.2(Spec. Acc)/°C, <18°C or>28°C	.	.
Safety: IEC 61010 and designed to meet UL61010 specifications	CAT IV 600V CAT III 1000V	CAT IV 600V CAT III 1000V
Maximum Conductor Size	10" coil/ 18" coil size	10" coil/ 18" coil size
Coil Diameter	7.5mm	7.5mm
Power Requirement: IEC LR03, AM4 or AAA size Battery x 2	.	.
Battery Life: In hours(ALKALINE Battery)	200	160
Size: 280mm(L) x 120mm(W) x 25mm(H)(10" coil size) 350mm(L) x 130mm(W) x 25mm(H)(18" coil size)	.	.
Weight: In grams	170/200	170/200
Included with instrument: Battery and User manual	.	.

Specifications subject to change without notice.

Copyright © 2014 APPA Tech., Corp. All rights reserved

Distrubuted by:



APPA TECHNOLOGY CORPORATION
 9F, 119-1 Pao-Zong Rd., Shintien, Taipei, 231, TAIWAN
 Tel: +886-2-29178820 Fax: +886-2-29170848
 E-mail: info@appatech.com · http://www.appatech.com
 ISO 9001 CERTIFIED

APPA SFLEX-D/T

Flexible Current Probe Meter



APPA[®]
 Advanced Instrument Technology Made Easy